



FLEXPASS

ARCH

A BOLD STATEMENT. THE ARCH COVER DESIGN PRODUCES A UNIQUE LOOK BY COMBINING SYMMETRICAL GRIDS AND COMPLEMENTARY ARCHES.



ARCH



AVAILABLE IN: BLACK GREY WHITE BEIGE

INDALA PROVIDES A COMPLETE PRODUCT PORTFOLIO WITH THE FLEXSECUR™ TECHNOLOGY - THE CONFIDENCE OF SECURITY BETWEEN CARD AND READER. SUPPORTED WITH INNOVATIVE DESIGN AND RESPONSIVE CUSTOMER CARE.

FLEXPASS™

An ASSA ABLOY Group company

ASSA ABLOY

SPECIFICATIONS

Size	Slim:	4.5" H x 1.7" W x 0.8" T (11.4cm x 4.3cm x 2.0cm)
	Wallswitch:	4.5" H x 3.0" W x 0.8" T (11.4cm x 7.6cm x 2.0cm)
	Mid-Range:	5.1" H x 6.1" W x 1.1" T (13.0cm x 15.5cm x 2.8cm)
Read Range	Slim:	Up to 5" (12.7cm) using FlexCard™ standard card
	Wallswitch:	Up to 5" (12.7cm) using FlexCard standard card
	Mid-Range:	Up to 12" (30.5cm) using FlexCard standard card
Input Voltage	Slim:	4-16 VDC at reader
	Mid-Range:	4-14 VDC at reader

Typical Current Draw

Off Metal:	Slim:	65 mA @ 12 V; 86 mA @ 5 VDC
	Wallswitch:	65 mA @ 12 V; 86 mA @ 5 VDC
	Mid-Range:	117 mA @ 12 V; 70 mA @ 5 VDC
On Metal:	Slim:	86 mA @ 12 V; 97 mA @ 5 VDC
	Wallswitch:	86 mA @ 12 V; 97 mA @ 5 VDC
	Mid-Range:	111 mA @ 12 V; 65 mA @ 5 VDC
Maximum:	Slim:	96 mA @ 12 V; 100 mA @ 5 VDC
	Wallswitch:	96 mA @ 12 V; 100 mA @ 5 VDC
	Mid-Range:	140 mA @ 12 V; 82 mA @ 5 VDC

Operating Temperature

-31° to +149°F (-35° to +65°C)

LED Indicator

Tri-color standard (red, green, amber)

Audio Tone

Standard, independently controllable (not tied to LED)

Output Formats

Wiegand, ABA Track II Magnetic Stripe, and Serial TTL (requires use of BIL 232/422 Module)

Frequency

125 kHz (excitation)

Read Time (26-bit)

200 ms (from read to data output)

Security

Various levels (configurable) FlexSecur™

Programming

Factory or field programmable via FlexPass

Colors

Black, Grey, White, Beige

Other Features

Self Test, QuickFlash, WatchDog

Product Description	Package* Part #	Bezel Only Part #	CEM Only Part #
Slim, Black	FP3511A	FPZ-3511A	FPC-0500A
Slim, Grey	FP3515A	FPZ-3515A	FPC-0500A
Slim, White	FP3516A	FPZ-3516A	FPC-0500A
Slim, Beige	FP3517A	FPZ-3517A	FPC-0500A
Wallswitch, Black	FP3521A	FPZ-3521A	FPC-0500A
Wallswitch, Grey	FP3525A	FPZ-3525A	FPC-0500A
Wallswitch, White	FP3526A	FPZ-3526A	FPC-0500A
Wallswitch, Beige	FP3527A	FPZ-3527A	FPC-0500A
Mid-range, Black	FP3231A	FPZ-3231A	FPC-0200A
Mid-range, Grey	FP3235A	FPZ-3235A	FPC-0200A
Mid-range, White	FP3236A	FPZ-3236A	FPC-0200A
Mid-range, Beige	FP3237A	FPZ-3237A	FPC-0200A
Mid-range, Black, Serial	FP3231S	FPZ-3231A	FPC-0200S
Mid-range, Grey, Serial	FP3235S	FPZ-3235A	FPC-0200S
Mid-range, White, Serial	FP3236S	FPZ-3236A	FPC-0200S
Mid-range, Beige, Serial	FP3237S	FPZ-3237A	FPC-0200S

*Packages include Core Electronics Module (CEM) and Bezel.




FlexISO



FlexKey



FlexCard



FlexISO XT

Credentials

The Indala FlexPass Arch is designed to work seamlessly with Indala FlexPass credentials such as the FlexISO™, FlexKey™, FlexCard, and FlexISO XT Durable Composite Card.

APPROVALS

UL 294/cUL, FCC Certification - United States, Canada Certification, CE Mark - Europe, Australia C-Tick, New Zealand/EMC

WARRANTY

Indala warrants this product against defects in material and workmanship under normal use and service. The warranty period commences with the date of shipment. See complete warranty statement for further details.

Read range stated when readers installed according to instructions. Read range may vary when mounted on metal and with different cover designs. Illumination colors may differ based on cover design color. Specifications subject to change without notice. Indala reserves the right to discontinue any product without notice.

Indala and FlexPass are registered trademarks of Indala, an ASSA ABLOY Group company. All other products or service names are the property of their respective trademark owners. © 2003 Indala. All rights reserved. Printed in the U.S.A. archds 10-2003



SLIM



WALLSWITCH



MID-RANGE

Headquarters
6850 B Santa Teresa Blvd.
San Jose, California 95119-1205 USA
Toll Free: 800-779-8663 (USA only)
Tech. Support: 800-646-3252 (USA only)
Phone: +1 408 361 4700
Fax: +1 408 361 4701

European Office
Wokingham, Berkshire UK
Phone: + 44 (0) 1189 121 780
Fax: +44 (0) 1189 121 790

Asia Pacific Office
Hong Kong
Phone: +852 2587 6008
Fax: +852 8343 7688

Mexico Office
Leon, Gto. México
Phone: +52 477 779 7784
Fax: +52 477 779 1493

Brazil Office
São Paulo, Brazil
Phone: +55 11 5576 6660
Fax: +55 11 5576 6661

Latin America Office
Buenos Aires, Argentina
Phone: +54 11 4857 1767
Fax : +54 11 4857 3573